

Thank you for purchasing the Sami wearable WS-2312. Read the instructions carefully to obtain optimum results and preserve it for future reference.

#### · DESCRIPTION OF THE WEARABLE.



#### CONTENTS

Wearable, USB cable, instruction manual.

#### **HOW TO CONTROL?**

- 1) Long press the power button to turn On/Off , short press to return to the home screen.
- 2) Tap &slide left/right to go to the different menus. Tap the icons to select them.
- 3) On the home screen, tap on the top of the screen and slide down to view the Date/Time/Bluetooth status/Battery status/Volume status; and on this interface, tap to quickly turn the Bluetooth On/Off, tap to quickly mute/un-mute the voice volume.

## CHARGING.

Connect the SMART WATCH to a computer or laptop via USB cable for charging. Kindly use only the USB cable included with the wearable. If you use a power adapter for charging, the output of the power adapter should be 5V,1A. Charging time: 2~3 hours. Please charge the device fully before using.

# GETTING STARTED:

#### - For Android

1) How to obtain the BT Connection APK (LEFUN DEVICE / LEFUN WEAR)

Please download the application from **www.sami.es**. For any technical support please write an email to info@sami.es

- 2) How to make the wearable pair with your Android smart phone?
- \*Firstly, turn on both the Bluetooth of your device and the Bluetooth of the wearable. Make the Bluetooth visible, and make it pair.

When installing the **LEFUN DEVICE/LEFUN WEAR** app on your Android smart phone, it must allow all the Application Permissions, allow the **LEFUN DEVICE/LEFUN WEAR** auto run.

The first time to run this smart watch FLUO, it will ask you to Enable Notifications, please tap OK and tap the **LEFUN DEVICE/LEFUN WEAR** and confirm OK..

On your Android smart phone, go to Settings --- > Accessibility --- > turn on the **LEFUN DEVICE/LEFUN WEAR** (If the **LEFUN DEVICE** isn't turn on here, it will not work successfully.)

\*Secondly, run the **LEFUN DEVICE/LEFUN WEAR APP** on the android, on the home page of **LEFUN DEVICE/LEFUN WEAR**, tap the left top menu--> then tap and select the first option(equipment name/connection status) ---> the tap the WS-2312, to make it pair.

**Note**: To avoid conflicts between different Bluetooth Connection APKs, you may need to uninstall all other similar Bluetooth Connection APKs before installing this APK (**LEFUN DEVICE** / **LEFUN WEAR**).

#### - For iPhone

1) How to obtain the BT Connection APP(LEFUN DEVICE APP)

On iPhone, please go to APP Store and search LEFUN DEVICE app and install it.

2) How to make the wearable pair with your iPhone?

\*First, turn on both the Bluetooth of the iPhone and the Bluetooth of the wearable. Make the Bluetooth visible, and make it pair.

When the Bluetooth is successfully paired with iPhone, on the iPhone Setting --- >tap Bluetooth ---- >you will see there is one WS-2312 connected.

\*Secondly, run the **LEFUN DEVICE APP** on the iPhone, on the home page of **LEFUN DEVICE**, tap the left top menu--> then tap and select the first option (Not connect for the present)--> then tap search --> then tap the WS-2312, to make it pair.

When the Bluetooth successfully paired with iPhone again, on the iPhone Setting --- >tap Bluetooth ---- >you will see there are two WS-2312 connected.

Now the wearable is successfully pairing with your iPhone.

**Notice**: On the FLUO smart watch you will need to tap Sync Date to sync all the data of Pedometer, Sleep Monitor, Heart Rate, etc. It won't automatically sync.

#### PRODUCT FEATURES.

#### · POWER KEY

Long press Power key for 2 seconds to Power on /off the wearable. Short press Power key to go back to home screen.

- ·SPEAKER. The wearable comes with an built in speaker.
- •TOUCH SCREEN. Capacitive round touch screen 1.54"
- · BUILT IN MICROPHONE.
- · HEART RATE SENSOR.
- ·CHARGING PORT. USB charging by means of USB cable (included).
- · HOME SCREEN INTERFACE

On Home Screen, tap and slide towards left or towards right to enter page of Applications; tap and slide towards left / right to go to the next page /previous page.

# · DIGITAL CLOCK

How to change the style of digital clock?

Long tap the screen on current displaying digital clock, when it zoom out, tap and slide towards left or towards right to choose different style of digital clock, tap OK to confirm it.

## ·BLUETOOTH (V 4.0).

Settings --- >BT settings --- > set Bluetooth on/off, and visibility. The bluetooth is for default OFF.

BT Connection ----> search device ---- >tap the name of BT device and make it pair

CONTACTS (PHONEBOOK)
DIALER

**CALL LOGS** 

MESSAGES -for Android to load all of your phone's local SMS. Not available for iOS

**NOTIFIER** -support to sync all push message notifications from your smart phone to the weak-ake, including notice of incoming SMS, WhatsApp message, Facebook message, Twitter message, Skype message, etc.

BT -search Bluetooth devices and pair

PEDOMETER
SLEEP (SLEEP MONITOR)
HEART RATE
SEDENTARY (SEDENTARY REMINDER)
LOST ALERT
FIND PHONE
ALARMS (ALARM CLOCK)
CALENDAR
MUSIC
CAMERA (REMOTE CAPTURE)

**APP** -QR codes for BT Connection APK. (The QR code is for Android only. For iOS please go to APP Store and search LEFUN DEVICE to find it and install it)

STOPWATCH
CALCULATOR
WEATHER
MOTION (GESTURE CONTROL)
DRINK (DRINK REMINDER)
SETTINGS

- -BT settings (set Bluetooth on/off, visibility)
- -Clock, Sound, Volume, Display
- -International (set language)
- -Reset (reset the weaker)

**BLOOD-PRESS (BLOOD PRESSURE TEST)** 

## \*WHAT BT SYNC FUNCTIONS CAN BE ACHIEVED FOR ANDROID DEVICES?

Dial/answer Phone Call
Sync Phonebook
BT Music Playing
Messaging /need APK to support
BT notice /need APK to support
BT camera/need APK to support
Find my device /need APK to support
Sync data of Pedometer/Sleep/Heart Rate /need APP to support

\*Notice: The BT Sync functions may vary with different versions of mobile OS.

## WHAT BT SYNC FUNCTIONS CAN BE ACHIEVED FOR IOS DEVICES?

Dial/answer Phone Call
Sync Phonebook
BT Music Playing
BT notice /need APP to support
BT camera/need APP to support
Find my device /need APP to support
Sync data of Pedometer/Sleep/Heart Rate/need APP to support

# TECHNICAL SPECIFICATIONS:

Display screen: Capacitive touch screen IPS 1.54".

Screen resolution: 240x240 pixels. Internal memory: 32 Mbit+ 32 Mbit

Charge I/O port: Micro USB 5 pin charging.

Battery: Built in Li-Polymer 300 mAh Stand by time: 100-120 hours Phone call working time: 3-6 hours.

Bluetooth: V4.0.

# **Declaration of Conformity**

# Hereby we,

Name of manufacturer: SANTOSHI SL

Address: CALLE FELIPE ASENJO N.56

Zip code & City: 28947 - FUENLABRADA ( MADRID )

Country: SPAIN

declare that this DoC is issued under our sole responsibility and that this product:

Product description: Smartwatch

Type designation(s): WS-2312

Trademark: SAMI WEARABLE

is in conformity with the relevant Union harmonization legislation:

DIRECTIVE EMC 2014/30/EU DIRECTIVE LVD 2014/35/EU

Standard CE-RED: DIRECTIVE 2014/53/EU

Standard ROHS: 2011/65/EC: restriction of dangerous substances.

with reference to the following standards applied:

EN60950-1/A2:2013

EN300328v1.8.1

EN301489-1v1.9.2

EN62479:2010

EN301489-1 V1.9.2 (2011-09)

EN301489-7 V1.3.1 (2005-11)

EN301489-17 V2.2.1 (2012-09)

Signature

Full name: VISHAL MIRPURI

Position: ADMINISTRATOR

Date: 07 / 05 / 2018